

**WSZ Series
Main Unit**

Model: WSZ-40MCT2-AC

**製品仕様書
Product Specifications**

This material and the information herein is the property of Fuji Electric Co.,Ltd. They shall be neither reproduced, copied, lent, or disclosed in any way whatsoever for the use of any third party, nor used for the manufacturing purposes without the express written consent of Fuji Electric Co.,Ltd.

**富士電機株式会社
Fuji Electric Co.,Ltd.**

REVISIONS				

	DATE	NAME	APPROVED	Fuji Electric Co.,Ltd	
DRAWN	2011-11-9	小塚	酒井	DWG NO.	WDS500051a 1/6
CHECKED	--				

1 .Main Unit 共通仕様
Specifications of Main Unit

Item		Specification	Note			
Execution Speed		0.33 us / per Sequence Command				
Program Capacity		20K Words				
Program Memory		SRAM + Lithium battery for Back-up	Option: FLASH ROM			
Sequence Command		36				
Application Command		300 (113 types)	Include Derived Commands			
Flow Chart (SFC) Command		4				
Single Point 《BIT Status》	X	Output Contact(DI)	X0 ~ X255 (256)	Corresponding to External Digital Input Point		
	Y	Output Relay(DO)	Y0 ~ Y255 (256)	Corresponding to External Digital Output Point		
	TR	Temporary Relay	TR0 ~ TR39 (40)			
	M	Internal Relay	Non-retentive	M0 ~ M799 (800)* M1400 ~ M1911 (512)	Can be configured as retentive type	
			Retentive	M800 ~ M1399 (600)*	Can be configured as non-retentive type	
		Special Relay	M1912 ~ M2001 (90)			
	S	Step Relay	Non-retentive	S0 ~ S499 (500)*	S20~S499 can be configured as retentive type	
			Retentive	S500 ~ S999 (500)*	Can be configured as non-retentive type	
	T	Timer "Time Up" Status Contact	T0 ~ T255 (256)			
	C	Counter "Count Up" Status Contact	C0 ~ C255 (256)			
Register 《WORD Data》	TMR	Current	0.01S Time base	T0 ~ T49 (50)*	T0 ~ T255 Numbers for each time base can be flexibly adjusted.	
		Time Value	0.1S Time base	T50 ~ T199 (150)*		
		Register	1S Time base	T200 ~ T255 (56)*		
	CTR	Current Counter Value Register	16-Bit	Retentive	C0 ~ C139 (140)*	Can be configured as non-retentive type
				Non-retentive	C140 ~ C199 (60)*	Can be configured as retentive type
			32-Bit	Retentive	C200 ~ C239 (40)*	Can be configured as non-retentive type
				Non-retentive	C240 ~ C255 (16)*	Can be configured as retentive type
	HR DR	Data Register	Retentive	R0 ~ R2999 (3000)*	Can be configured as non-retentive type	
				D0 ~ D3999 (4000)		
	Non-retentive		R3000 ~ R3839 (840)*	Can be configured as retentive type		
			HR ROR	Retentive	R5000 ~ R8071 (3072)*	When not configured as ROR, it can serve as normal register (for read/write)
	Read-only Register	R5000 ~ R8071 can be configured as ROR, default setting is (0)*		ROR is stored in special ROR area and not consume program space		
	File Register	F0 ~ F8191 (8192)*	Must save/retrieved via special commands			
	IR	Input register	R3840 ~ R3903 (64)	Corresponding to external numeric input		
	OR	Output Register	R3904 ~ R3967 (64)	Corresponding to external numeric output		
	SR	Special System Register	R3968 ~ R4167 (197) D4000 ~ D4095 (96)	Except R4152 ~ 4154		
	Special Register	0.1ms High Speed Timer register		R4152 ~ R4154 (3)		
		High Speed Counter Register	Hardware(4 sets)	DR4096 ~ DR4110 (4x4)		
Software (4 sets)			DR4112 ~ DR4126 (4x4)			
Real Time Calendar Register		R4128 (sec)	R4128 (min)	R4130 (hour)	R4131 (day)	Accuracy : ±20 seconds per day
R4132 (month)	R4133 (year)	R4134 (week)				
XR	Index Register	V Z (2), P0 ~ P9 (10)				
Interrupt Control	External Interrupt Control		32 (16 point input positive/negative edges)			
	Internal Interrupt Control		8 (1, 2 3, 4, 5, 10, 50, 100 ms)			
0.1 ms High Speed Timer (HST)		1 (16 bits), 4 (32 bits, derived from HHSC)				

This material and the information herein is the property of Fuji Electric Co.,Ltd. They shall be neither reproduced, copied, lent, or disclosed in any way whatsoever for the use of any third party, nor used for the manufacturing purposes without the express written consent of Fuji Electric Co.,Ltd.

REVISIONS			
-----------	--	--	--

	DATE	NAME	APPROVED	Fuji Electric Co.,Ltd		
DRAWN	2011-11-9	小塚	酒井			
CHECKED	--					
					DWG.NO.	WDS500051a

This material and the information herein is the property of Fuji Electric Co.,Ltd. They shall be neither reproduced, copied, lent, or disclosed in any way whatsoever for the use of any third party, nor used for the manufacturing purposes without the express written consent of Fuji Electric Co.,Ltd.

High Speed Counter	Hardware High Speed Counter (HHSC) /32Points	Channels	Total 4		<ul style="list-style-type: none"> • Total number of HHSC and SHSC is 8 • HHSC can change into High Speed Timer with 32 bits/0.1ms Time base.
			Up to 4	Up to 2	
		Counting modes	8 modes (U/D, U/D×2, P/R, P/R×2, A/B, A/B×2, A/B×3, A/B×4)		
	Counting frequency	Up to 200KHz (single-end input)	Up to 20KHz (single-end input)		
	Software High Speed Counter (SHSC) /32Points	Channels	Up to 4		
		Counting modes	3 modes (U/D, P/R, A/B)		
Counting frequency		Maximum sum up to 5KHz			
Communication Interface	Port0 (RS232)		Communication Speed 4.8Kbps ~ 921.6Kbps (9.6Kbps)*		
	Port1(RS232), Port2(RS485)		Communication Speed 4.8Kbps ~ 921.6Kbps (9.6Kbps)*		Port1 ~ 2 talk Original Modbus RTU Master/Slave Communication Protocol
NC Positioning Output (PSO)	Number of Axes		Total 4		
			Up to 4	Up to 2	
	Output Frequency		200KHz single-end transistor output	20KHz single-end transistor output	
	Output Pulse Mode		3 modes (U/D, P/R, A/B)		
	Positioning Language		Special Positioning Programming Language		
HSPWM Output	Number of Points		Up to 4		
	Output Frequency		72Hz ~ 18.432KHz (with 0.1 resolution) 720Hz ~ 184.32KHz (with 1 resolution)		
Captured input	Points		Max.36 points (all of main units have the feature)		
	Captured pulse width	> 10 μs (super high speed/high speed input)			
		> 47 μs (medium speed input)			
	> 470 μs (mid/low speed input)				
Setting of Digital Filter	X0 ~ X15	Frequency 14KHz ~ 1.8MHz		Chosen by frequency at high frequencies	
		Time constant 0 ~ 1.5 ms/0 ~ 15 ms, adjustable by step of 0.1 ms/1 ms		Chosen by time constant at low frequencies	
	X16 ~ X35	Time constant 1 ms~15 ms, adjustable by step of 1ms			

2. 入出力仕様

Digital Input and Output Specifications

DI: 24 points / DO: 16 points

For more DI/DO information, see the next pages.

REVISIONS			
-----------	--	--	--

	DATE	NAME	APPROVED	Fuji Electric Co.,Ltd	
DRAWN	2011-11-9	小塚	酒井		
CHECKED	--				
					DWG NO.

入力仕様
Specifications of Digital Input Circuit

Item Specifications		24 VDC Single-end Input				
		Main Unit			Expansion Unit	
		High Speed (HSC)	Medium Speed (HSC)	Midium low Speed (Capture input)	Low Speed	
Maximum input frequency / Accumulated time		200KHz	20KHz (HHSC)	Total 5KHz (SHSC)	0.47ms	4.7ms
Input Signal Voltage		24 VDC±10%				
Input Current Threshold	ON Current	8 mA	4 mA		2.3 mA	
	OFF Current	2 mA	1.5 mA		0.9 mA	
Maximum Input current		10.5 mA	7.6 mA		4.5 mA	
Input Status Indication		Displayed by LED: Lit when "ON", dark when "OFF"				
Isolation Type		Photo coupler signal isolation				
SINK/SRCE Wiring		Via variation of internal common terminal S/S and external common wiring				
List of Input Response Speed for Various Models	WSZ-24MCT2-AC	4(X0,1,4,5)	4 (X8,9,12,13)	6 (X2,3,6,7,10,11)	—	—
	WSZ-32MCT2-AC	6(X0,1,4,5,8,9)	2 (X12,13)	8 (X2,3,6,7,10,11,14,15)	4(X16~19)	—
	WSZ-40MCT2-AC	6(X0,1,4,5,8,9)	2 (X12,13)	8 (X2,3,6,7,10,11,14,15)	8(X16~23)	—
	WSZ-60MCT2-AC	8(X0,1,4,5,8,9,12,13)	—	8 (X2,3,6,7,10,11,14,15)	20(X16~35)	—
	Expansion Unit	—	—	—	—	All Input Points
Noise Filtering Time Constant		DHF(0 ~ 15ms) + AHF(0.47µs)	DHF(0 ~ 15ms) + AHF(4.7µs)	DHF(1 ~ 15ms) + AHF(0.47ms)	AHF(4.7ms)	

HSC : High Speed Counter
 HHSC : Hardware High Speed Counter
 SHSC : Software High Speed Counter
 DHF Digital Hardware Filter
 AHF Analog Hardware Filter

This material and the information herein is the property of Fuji Electric Co.,Ltd. They shall be neither reproduced, copied, lent, or disclosed in any way whatsoever for the use of any third party, nor used for the manufacturing purposes without the express written consent of Fuji Electric Co.,Ltd.

REVISIONS	DATE	NAME	APPROVED	Fuji Electric Co.,Ltd	
	DRAWN	2011-11-9	小塚		
	CHECKED	-	-	DWG.NO.	WDS500051a 4/6

出力仕様
Specifications of Digital Output Circuit

Item Specification	Item	Single-End Transistor Output			
		Main Unit			Expansion Unit
		High Speed	Medium Speed	Low Speed	Low Speed
Maximum output Frequency *		200KHz	20KHz	On/Off	On/Off
Working Voltage		5 ~ 30 VDC			
Maximum Load Current	Resistive	0.5 A			0.1 A
	Inductive				
Maximum Voltage Drop / Conducting resistance		0.6 V	2.2 V		
Leakage Current		0.1 mA / 30 VDC			
Maximum Output Delay Time	ON OFF	2μs	15 μs		
	OFF ON		30 μs		
Output Status Indication		LED is bit when "ON", dark when "OFF"			
Over Current Protection		N/A			
Isolation Type		Photo Coupler Isolation,500VAC,1minute			
Output type		SINK			
List of output Response Speed for Various Models	WSZ-24MCT2-AC	4(Y0~3)	4(Y4~7)	2(Y8,9)	—
	WSZ-32MCT2-AC	6(Y0~5)	2(Y6,7)	4(Y8~11)	—
	WSZ-40MCT2-AC	6(Y0~5)	2(Y6,7)	8(Y8~15)	—
	WSZ-60MCT2-AC	8(Y0~7)	—	16(Y8~23)	—
	Expansion Unit	—	—	—	All output Points

* Half of the maximum frequency while A/B phase output

This material and the information herein is the property of Fuji Electric Co.,Ltd. They shall be neither reproduced, copied, lent, or disclosed in any way whatsoever for the use of any third party, nor used for the manufacturing purposes without the express written consent of Fuji Electric Co.,Ltd.

REVISIONS			
-----------	--	--	--

	DATE	NAME	APPROVED	Fuji Electric Co.,Ltd		
DRAWN	2011-11-9	小塚	酒井			
CHECKED	--					
					DWG.NO.	WDS500051a

3. 環境仕様

Environmental Specifications

Item		Specification		Note
Operating Ambient Temperature	Enclosure equipment	Minimum	5°C	Permanent Installation
		Maximum	40°C	
	Open equipment	Minimum	5°C	
		Maximum	55°C	
Storage Temperature		-25°C +70°C		
Relative Humidity (non-condensing, RH-2)		5% ~ 95%		
Pollution Level		Degree II		
Corrosion Resistance		By IEC-68 Standard		
Altitude		2000 m		
Vibration	Fixated by DIN RAIL	0.5G, for 2 hours each along the 3 axes		
	Secured by screws	2G, for 2 hours each along the 3 axes		
Shock		10G, 3 times each along the 3 axes		
Noise Suppression		1500Vp-p, width 1us		
Withstand Voltage		1500VAC, 1 minute		L, N to any terminal

This material and the information herein is the property of Fuji Electric Co.,Ltd. They shall be neither reproduced, copied, lent or disclosed in any way whatsoever for the use of any third party, nor used for the manufacturing purposes without the express written consent of Fuji Electric Co.,Ltd.

REVISIONS			
-----------	--	--	--

	DATE	NAME	APPROVED	Fuji Electric Co.,Ltd	
DRAWN	2011-11-9	小塚	酒井	DWG NO.	WDS500051a 6/6
CHECKED	--				